

Leakage Circuit Breaker

IEC61008-1,GB16916.1

IEC/EN61008-2-1,IEC/EN62423

GYL9 RCCB

Scope of application

GYL9 residual current circuit breaker (without overcurrent protection) is suitable for AC 50Hz, rated voltage 240V for two poles, 415V for four poles, and rated current up to 80A. It can quickly cut off the fault power in a very short time,

To protect the safety of people and electrical equipment, it can also be used for infrequent switching of lines.

It's suitable for terminal distribution lines in commercial office buildings, residential and general industrial use.

Compliant with: IEC61008-1, GB16916.1



Technical Parameter

Electrical Characteristics									
Classification		Protection type		Poles	Rated current (In)	Rated sensitivity (I Δ n)	Sensitivity		Rated voltage (Ue)
AC	A	ELE	ELM				Instantaneous	Delayed	
■	■	■	■	1P+N,3P+N	25, 40, 63, 80A	10, 30, 100, 300mA	■	■	1P+N:240V~ 3P+N:415V~
Rated insulation voltage (Ui)	Rated frequency	Rated impulse withstand voltage (Uimp)	Rated residual making and breaking capacity I Δ m	Short-circuit current Inc=I Δ c	Rated residual non-operating current	Break time(Instantaneous)			
						Residual current I Δ =1I Δ n	Residual current I Δ =2I Δ n	Residual current I Δ =5I Δ n	
500V	50/60Hz	4kV	500A (below 63A) 10In(63A and above)	10kA (below 63A) 10kA(63A and above)	0.5I Δ n	0.1s	0.08s	0.04s	

Mechanical properties

Mechanical life /Electric life	Protection class		Ambient temperature	Storage temperature
	Direct install	In distribution box		
4000	Ip20	Ip40	-25°C+60°C	-25°C+70°C

Other characteristics

Wiring size		Contact Status Indication	Fault Indication	Circuit identification	Connection	Assemblable accessories
Copper/Hard Wire	Cord/Hoop Terminals					
1-35mm ²	1-25mm ²	—	■	—	Top and bottom(ELM) Top line(ELE)	—

GYL9-B RCCB

Scope of application

GYL9-B residual current operated circuit breaker is suitable for AC 50Hz, rated voltage 240V for two poles, 415V for four poles, rated current up to 63A, used to detect AC leakage, pulsating DC leakage, smooth DC leakage, compound wave leakage and high frequency leakage current up to 1kHz. When people come to electric shock or the leakage current of the circuit exceeds the specified value, it automatically cuts off the faulty power supply in a very short time to protect the safety of people and electrical equipment. It can also be used for infrequent switching operations in normal condition.

Compliant with: IEC62423,IEC61008-1,GB22794,GB16916.1

Technical Parameter



Electrical Characteristics						
Classification	Application		Poles	Rated current (In)	Rated sensitivity (I Δ n)	Rated Voltage (Ue)
B	Electric car charging station, charging pile	Equipment circuit controlled by three-phase inverter	1P+N,3P+N	25, 40, 63, 80A	30, 100, 300mA	1P+N:240V~ 3P+N:415V~
Rated Insulation voltage (Ui)	Rated frequency	Rated impulse withstand voltage (Uimp)	Rated short-circuit current Inc=rated residual short circuit current Δ I m	Rated residual connecting and breaking capacity Inc=I Δ c	Rated residual non-operating current	
500V	50/60Hz	4kV	500A (63A below) 10In (63A and above)	6kA	0.5I Δ n	

Mechanical properties

Mechanical life /electrical life	Protection class		Working ambient temperature	Storage temperature
	Installed directly	Installed in the distribution box		
4000	Ip20	Ip40	-25°C+60°C	-25°C+70°C

Other characteristics

Wiring size		Contact status Indication	Fault Indication	Circuit identification
Copper/ hard wire	Cord/hoop terminals			
1-35mm ²	1-25mm ²	—	■	—